

# NC4000 Series TECHNICAL INFORMATION

<b>SIZE AND APPROX. WEIGHT:</b>	<b>NC4010</b>	<b>NC4106</b>	<b>NC4068</b>	<b>NC4030</b>	<b>NC4073</b>
Weight:	75Kg	36Kg	40Kg	18.85Kg	37.05Kg
Size:	545mmW 1000mmH 575mmD	265mmW 995mmH 250mmD	265mmW 1295mmH 250mmD	300mmW 760mmH 300mmD	280mmW 1890mmH 310mmD
<b>CONNECTIONS:</b>					
Power:	IEC (internally Fused)	IEC (internally Fused)	IEC (internally Fused)	IEC (internally Fused)	IEC (internally Fused)
COAX Connection: (NC4030 only)	N/A	N/A	N/A	5 x BNC connectors one for each compartment	N/A
Ethernet port: (for remote access)	RJ45	RJ45	RJ45	RJ45	RJ45
<b>POWER REQUIREMENTS:</b>					
Input range:	220-240VAC 50Hz	220-240VAC 50Hz	220-240VAC 50Hz	220-240VAC 50Hz	220-240VAC 50Hz
<b>COMPATIBILITY:</b>					
Compatible with:	Motorola /Sepura Handheld Radios & laptops	Motorola & Sepura Handheld Radios	Motorola & Sepura Handheld Radios	Sepura SRG/SRM	N/A
<b>REMOTE PROGRAMING OPTIONS:</b>					
Parity: None, Even, Odd, Space, Mark Data bits: 5, 6, 7, 8 Stop bits : 1, 1.5, 2 Flow control: RTS/CTS, DSR/DTR (for RS-232 only), XON/XOFF Transmission speed: 50 bps to 921.6 Kbps Bandwidth requirements: 50Kbytes when programing at 115200 baud rate				N/A	
Requires a static IP address				N/A	